Datasheet for: SU3667

Product Type: 230v portable Tool transformers

3000VA 110v to 230v with 2 x 16A Schuko sockets Stepup transformer



VA	3000
Input Voltage	110
Input Termination	Mains lead with Yellow 32amp plug
Input Current	27
amps	16
Output Voltage	230
Output Notes	3000va continuous rating
Output Termination	Two Grey 16A EU Schuko sockets
Product Case	701 Tough GRP case with carrying handle IP44
Dimension	Ht:280 W:200 D:200
Weight	13kg
Primary Protection	Push to reset circuit breaker SP8
Surge Protection	SL32 Surge Limiter
Product Type	Autowound transformer Conforms to EN61558-2-13 CE & RoHS
Notes	British Built

Commodity code: 851539130

RoHS Certificate: Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+ Bifenil Polybromurate (PBB) Ethere Difenil Polybromurate (PEDE)

Declaration of Conformity: Airlink Transformers declare that the product SU3667 conforms to current European safety and EMC regulation EN61558-2-6 (Safety Isolating transformer) CE & RoHS compliant. Manufactured to Class A 105degC.

Declaration by the Exporter: The exporter of the product covered by this document declares that these products are of EU preferential origin.
29/11/2026

www.airlinktransformers.com - VAT No. 573 1888 10
Airlink Transformers is a trading name of Albury Services Ltd company reg No 2666478
14 Capital Place, Lovet Road, The Pinnacles, Harlow, Essex, UK, CM19 5AS
01279 431865 | sales@airlinktransformers.com