Datasheet for: SU5000

Product Type: 230v portable Tool transformers

5000VA 110v to 230v step-up transformer with 2 x 16A Blue socket transformer



VA	5000
Input Voltage	110
Input Termination	2 meter mains lead with 63A inline plug
Input Current	45
amps	22
Output Voltage	230
Output Notes	4000va continuous rating
Output Termination	Two Blue 230v 16amp 3pin sockets
Product Case	801 Tough GRP case with carrying handle IP44
Dimension	Ht:280 W:340 D:260
Weight	22kg
Primary Protection	Push to reset circuit breaker SP20
Surge Protection	SL35 Surge Limiter
Product Type	Autowound transformer Conforms to EN61558-2-13 CE & RoHS
Notes	British Built

Commodity code: 851539130

RoHS Certificate: Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+ Bifenil Polybromurate (PBB) Ethere Difenil Polybromurate (PEDE)

Declaration of Conformity: Airlink Transformers declare that the product SU5000 conforms to current European safety and EMC regulation EN61558-2-6 (Safety Isolating transformer) CE & RoHS compliant. Manufactured to Class A 105degC.

Declaration by the Exporter: The exporter of the product covered by this document declares that these products are of EU preferential origin.
29/11/2026

www.airlinktransformers.com - VAT No. 573 1888 10
Airlink Transformers is a trading name of Albury Services Ltd company reg No 2666478
14 Capital Place, Lovet Road, The Pinnacles, Harlow, Essex, UK, CM19 5AS
01279 431865 | sales@airlinktransformers.com