

Datasheet for: EU-JA1000

Product Type: Use Japanese Appliances in Europe

1000va 230v Schuko to 100v Voltage Converter with two Japanese sockets



| | |
|--------------------|--|
| VA | 1000 |
| Input Voltage | 230 |
| Input Termination | 3 pin Schuko plug |
| Input Current | 4 |
| amps | 10 |
| Output Voltage | 100 |
| Output Termination | Two 100v Japanese 3pin socket |
| Product Case | UKM1 Medium Grey steel case |
| Dimension | Ht:115 L:250 W:190 (mm) |
| Weight | 6kg |
| Primary Protection | Push to reset circuit breaker SP12 |
| Product Type | Autowound transformer Conforms to EN61558-2-13 CE & RoHS |

Commodity code: 851539130

RoHS Certificate: Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+ Bifenil Polybromurate (PBB) Ether Difenil Polybromurate (PEDE)

Declaration of Conformity: Airlink Transformers declare that the product EU-JA1000 conforms to current European safety and EMC regulation EN61558-2-6 (Safety Isolating transformer) CE & RoHS compliant. Manufactured to Class A 105degC.

Declaration by the Exporter: The exporter of the product covered by this document declares that these products are of EU preferential origin.
16/04/2026

